E-ISSN: 1116 – 2716 P-ISSN: 3026-8214
MPRI-JAAE | INTERNATIONAL JOURNAL OF APPLIED & ADVANCED ENGINEERING RES.
VOL. 05 NO. 5 - JULY, 2024

EXPLORING MICROSTRIP FEEDING TECHNIQUES FOR 5G AND BEYOND ENHANCED ANTENNA PERFORMANCE

[1]SAFIYA YUSUF; [2]SIKIRU O. ZAKARIYYA; & [3]AGBON, E. E.

[1]Department of Electrical and Electronics Engineering, Kaduna Polytechnic, Kaduna. [2]Department of Electrical and Electronics Engineering, University of Ilorin, Ilorin, Kwara State, Nigeria. [3]Department of Electronics and Telecommunications Engineering. Ahmadu Bello University, Zaria

Corresponding Author: safiyayusuf2010@gmail.com

Abstract

This research paper investigates and analyzes various microstrip feeding techniques with the aim of enhancing antenna performance. Microstrip antennas have gained widespread use in wireless communication systems due to their compact form factor and versatility. However, achieving optimal performance in terms of gain, bandwidth, and radiation pattern remains a challenging task. The study delves into different microstrip feeding techniques, including aperture-coupled, coaxial probe, inset-fed, and proximity-coupled methods. Each technique's theoretical background, advantages, and limitations are thoroughly examined. Furthermore, practical implementations and design considerations are discussed to provide a comprehensive overview of the microstrip feeding approaches. Through a comparative analysis of these techniques, this research aims to offer valuable insights into selecting the most suitable feeding method for specific antenna applications. The study also considers recent advancements and emerging trends in microstrip feeding techniques, emphasizing their impact on modern wireless communication systems. Ultimately, this research contributes to the ongoing efforts to enhance antenna performance, enabling improved signal quality and communication reliability in various applications, including 5G networks, satellite communication, and IoT devices.

Keywords: Antenna, Microstrip, Technique and Communication.

EDITOR-IN-CHIEF
Prof. Saeid Eslamian [IRAN]

Introduction

In the realm of modern wireless communication, microstrip antennas have become indispensable components, providing efficient and compact solutions for a wide range of applications. These planar antennas, designed to operate at microwave frequencies, offer advantages such as low profile, lightweight construction, and ease of integration into various devices and systems (Tesnim *et al.,* (2019). However, the successful deployment of microstrip antennas hinges not only on their design and geometry but also on the techniques used to feed energy or signals into them. The process of feeding energy into microstrip antennas, known as microstrip feeding techniques, is a critical aspect of their design and functionality. These techniques determine crucial antenna parameters such as impedance matching, radiation characteristics, and overall performance. With an array of feeding methods at their disposal, engineers must carefully select the most appropriate technique to meet the specific requirements of their application (Tesnim *et al.,* (2019).

This paper explores the fundamental principles and common microstrip feeding techniques that have emerged as essential tools in the design and optimization of microstrip antennas. These techniques encompass a range of configurations and methods, each offering distinct advantages and trade-offs. Among them are traditional approaches like the coaxial feed and microstrip line feed, as well as innovative solutions like aperture-coupled, proximity-coupled, and inverted microstrip feeds. Additionally, we delve into advanced techniques like aperture-backed slot feed, coplanar waveguide (CPW) feed, and balanced feed structures. Each of these techniques plays a pivotal role in addressing challenges related to impedance matching, radiation efficiency, and interference management. The choice of a feeding method depends on various factors, including the desired frequency of operation, bandwidth requirements, and the need for specialized features like broadband impedance matching or reduced common-mode radiation.

In the pages that follow, we will embark on an exploration of these microstrip feeding techniques, shedding light on their underlying principles, advantages, and practical considerations. By gaining a deeper understanding of these methods, engineers and researchers can harness the full potential of microstrip antennas, contributing to the continued evolution of wireless communication systems and other microwave applications.

REVIEW OF COCNEPTS AND SIMILAR WORKS

The subsection presents the review of fundamental concepts that are related to this study. Also, a critical review of work was carried out which served as a platform for the study.

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

Concepts of Microstrip Patch Antenna

Microstrip antennas, also known as patch antennas, are a type of planar antenna commonly used in modern wireless communication systems and microwave devices (Christina, 2021). They are characterized by their flat, compact, and lightweight structure, making them suitable for integration into various electronic systems. The framework of a microstrip patch antenna is given in Figure 1.



Figure 1: A Microstrip Patch Antenna (Christina, 2021)

The concept of microstrip antennas revolves around their design and operation principles, including their structure, advantages, and applications. Microstrip antennas typically consist of several key components which include (Christina, 2021):

1. Radiating Patch: The radiating element of a microstrip antenna is a metallic patch typically made of copper or other conductive materials. This patch is usually square, rectangular, or circular in shape and is positioned on the top surface of a dielectric substrate.
2. Dielectric Substrate: Beneath the radiating patch, there is a dielectric substrate, which serves to support the patch and provide electrical isolation from the ground plane. The choice of substrate material and its thickness can significantly impact the antenna's performance.
3. Ground Plane: On the bottom side of the substrate, a ground plane is placed, which acts as a reflector for the electromagnetic waves and enhances antenna efficiency.
4. Feeding Mechanism: A feeding mechanism, such as a microstrip transmission line, coaxial cable, or other means, is used to introduce energy or signals into the radiating patch.

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

Operation Principles of Microstrip Patch Antenna

The operation of microstrip antennas is based on the principles of electromagnetic wave propagation and radiation. When electromagnetic signals are fed into the radiating patch through the feeding mechanism, they create an electric field across the patch (Christina, 2021). This electric field generates electromagnetic waves that propagate away from the antenna, radiating into free space. The physical dimensions of the patch, the dielectric properties of the substrate, and the frequency of operation determine the antenna's radiation pattern, impedance, and other characteristics. The advantages of microstrip antennas are given as follows (Shereen *et al.,* 2022):

1. Compact Size: Their planar structure allows microstrip antennas to be compact and suitable for integration into space-constrained devices.
2. Lightweight: Microstrip antennas are lightweight due to their thin, flat design, making them ideal for portable and weight-sensitive applications.
3. Low Profile: They have a low profile and can be mounted flush with the surface of a device or circuit board.
4. Ease of Fabrication: Microstrip antennas are relatively easy to fabricate using standard printed circuit board (PCB) manufacturing techniques.
5. Frequency Agility: Their resonant frequency can be adjusted by changing the dimensions of the radiating patch and substrate, making them versatile for various frequency bands.

Applications of Microstrip Antennas

Microstrip antennas find applications in a wide range of fields, which include the following (Mishra *et al.,* 2022):

1. Wireless Communication: They are used in smartphones, Wi-Fi routers, Bluetooth devices, and other wireless communication systems.
2. Satellite Communication: Microstrip antennas are employed in satellite communication systems for data transmission and reception.
3. Radar Systems: They are used in radar systems for target detection, tracking, and imaging.
4. Aerospace and Defense: Microstrip antennas are integrated into aircraft, drones, and military vehicles for communication and surveillance.
5. RFID Technology: They are used in radio-frequency identification (RFID) systems for tracking and identification purposes.

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

In summary, microstrip antennas are essential components in modern wireless communication and microwave technologies. Their concept revolves around their planar design, operation principles, advantages, and diverse applications across various industries. Their compact size, lightweight nature, and adaptability to different frequency bands make them a valuable choice for a wide range of wireless communication devices and systems.

Concept of Microstrip Antenna Feeding Technique

The concept of microstrip antenna feeding techniques is a fundamental aspect of designing and operating microstrip antennas. Microstrip antennas, often referred to as patch antennas, are widely used in modern wireless communication systems due to their compact size, low profile, and ease of integration into electronic devices. The feeding technique determines how electromagnetic energy is coupled into and radiated from the antenna, playing a crucial role in its performance (Christina, 2021). Microstrip antennas are planar antennas that operate at microwave frequencies. They consist of a radiating patch, which is usually a metallic conductor, and a ground plane separated by a dielectric substrate. Microstrip antennas are popular in applications such as mobile phones, Wi-Fi routers, satellite communication, radar systems, and more. The importance of feeding techniques are as follows:

1. Feeding techniques dictate how power or signals are introduced into the antenna structure.
2. The choice of feeding technique impacts various antenna parameters, including radiation pattern, impedance matching, gain, bandwidth, and efficiency.
3. Different feeding techniques are suitable for different applications and design goals.

Antenna Feeding Techniques

Microstrip antennas offer a wide range of feeding techniques to connect them to signal sources while achieving specific performance goals. The common types of antennas feeding techniques are discussed as follows (Basal and Gupta, 2020):

Coaxial Feed for Microstrip Antennas

Coaxial feed is one of the primary feeding techniques used in microstrip antennas. In this method, a coaxial cable is directly connected to the radiating patch and the ground plane

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

of the antenna. While it offers simplicity and ease of implementation, it can pose challenges related to impedance matching and overall antenna performance. A sample of a coaxial feed antenna technique and magnitude plot is given in Figure 2



a. Framework b. Magnitude Plot

Figure 2: Microstrip line Feed (Basal and Gupta, 2020)

The details of the coaxial feed are as follows (Basal and Gupta, 2020):

i. **Configuration and Connection**: In a coaxial feed setup, the central conductor of the coaxial cable is connected to the radiating element (patch) of the microstrip antenna. The outer conductor or shield of the coaxial cable is typically connected to the ground plane of the antenna.

ii. **Simplicity and Advantages:** Coaxial feed is straightforward to implement, making it a popular choice for many microstrip antenna designs. It provides a direct and sturdy connection between the antenna and the feedline, ensuring reliable signal transmission.

iii. **Impedance Matching Challenges**: One of the key challenges associated with coaxial feed is impedance matching. Microstrip antennas are typically designed to operate at specific frequencies, and achieving a good impedance match between the antenna and the feedline is crucial for optimal performance. Coaxial cables inherently have a characteristic impedance (usually 50 or 75 ohms), and this impedance may not match the input impedance of the microstrip antenna, which can be different due to design factors.

iv. **Impedance Discrepancy**: The impedance mismatch between the coaxial cable and the antenna can result in several issues (Tasnim *et al.*, 2019):

   a. Reflection of signals: When there is an impedance mismatch, a portion of the signal traveling along the coaxial cable is reflected back towards the source. This reduces the efficiency of the antenna system.

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

b. Loss of power: Impedance mismatch can lead to power loss, reducing the antenna's gain and radiation efficiency.
c. Narrow bandwidth: Coaxial feed may limit the bandwidth of the microstrip antenna, making it less versatile for applications that require a broader frequency range.

v. **Mitigating Impedance Mismatch:** To address impedance matching challenges in coaxial feed setups, various techniques can be employed:
   a. Matching networks: Matching networks, such as baluns and impedance transformers, can be used to bridge the impedance gap between the coaxial cable and the antenna.
   b. Tapered transitions: Gradual transitions from coaxial cable to microstrip can help reduce reflections.
   c. Adjusting dimensions: Altering the dimensions of the patch and feedline can sometimes improve impedance matching.

vi. **Applications:** Despite its impedance matching challenges, coaxial feed is widely used in microstrip antennas for applications where simplicity and ease of implementation are more critical than absolute performance. It is commonly found in consumer electronic devices, wireless routers, and small communication systems (Kashyap *et al.,* 2020).

Microstrip Line Feed for Microstrip Antennas

The microstrip line feed is a popular technique used to connect microstrip antennas to the signal source. This method involves using a microstrip transmission line to feed energy or signals into the antenna. It offers several advantages, including improved impedance matching, and is commonly employed in patch antennas. Figure 3a shows a framework of a microstrip line feed for microstrip antennas. Figure 3b shows the magnitude with microstrip feed. The details are as follows (Kashyap *et al.,* 2020):

i. **Configuration and Connection**: In the microstrip line feed technique, a microstrip transmission line is used to connect the antenna's radiating patch to the signal source or feedline. The microstrip line is typically a narrow strip of conductive material (such as copper) placed on the surface of a dielectric substrate. One end of the microstrip line is connected to the radiating element (patch), and the other end is connected to the signal source or feedline.

ii. **Advantages of Microstrip Line Feed**
   a. Improved Impedance Matching: One of the primary advantages of using microstrip line feed is its ability to achieve better impedance matching. Impedance matching is critical for efficient power transfer and optimal antenna performance. By carefully designing the microstrip line dimensions, engineers can tailor the impedance of the feedline to match that of the antenna, reducing reflection and power loss.

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

b. Versatility in Patch Antennas: Microstrip line feed is commonly employed in patch antennas, which are a type of microstrip antenna with a flat radiating patch. Patch antennas are popular due to their compact size and ease of integration into various electronic devices. The microstrip line feed complements these advantages by offering an effective means of feeding energy into the patch.



a. Framework b. Magnitude Plot

Figure 3: Microstrip Line Feed (Kashyap *et al.*, 2020)

iii. **Design Considerations**: When designing a microstrip line feed for a patch antenna, engineers must carefully consider the dimensions of the microstrip line and the dielectric substrate. These dimensions play a crucial role in determining the impedance of the feedline. The width and thickness of the microstrip line, as well as the dielectric constant of the substrate material, are key parameters that affect impedance matching.

iv. **Broadband and Multiband Applications:** Microstrip line feed can be designed to work over a broad range of frequencies, making it suitable for broadband and multiband applications. Engineers can optimize the dimensions of the microstrip line to achieve impedance matching across multiple frequency bands, enhancing the antenna's versatility.

v. **Limitations:** While microstrip line feed offers excellent impedance matching and versatility, it may not be the ideal choice for all types of microstrip antennas. In some cases, other feeding techniques, such as aperture-coupled feed or proximity-coupled feed, may be preferred, depending on the specific requirements of the antenna design and application.

In conclusion, the microstrip line feed technique is a valuable method for connecting microstrip antennas, particularly patch antennas, to the signal source. It offers improved impedance matching, versatility in design, and the pote ntial for broadband and

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

multiband applications. Engineers can fine-tune the dimensions of the microstrip line to optimize antenna performance and achieve efficient power transfer.

1. **Aperture-Coupled Feed**

The following are the details of this feeding technique (Basal and Gupta, 2020):

2. **Principle:** Aperture-coupled feed involves creating an aperture or slot in the ground plane located beneath the microstrip patch antenna. Energy from the microstrip transmission line is coupled to the patch through this aperture. Figure 4 shows an aperture-coupled feed antenna and the magnitude graph at various frequencies.
   - i. **Impedance Matching:** This technique is known for its ability to achieve good impedance matching between the feedline and the antenna. The aperture's dimensions can be optimized to ensure efficient power transfer and minimal reflection.
   - ii. **Reduction in Radiation from Feed Line:** Aperture coupling significantly reduces radiation from the feed line. This minimizes interference between the feed line and the radiating element, improving the antenna's radiation pattern and efficiency.
   - iii. **Applications:** Aperture-coupled feed is commonly used in patch antennas and other microstrip antenna designs where impedance matching and reduced feed line interference are critical.



a. Framework b. Magnitude Plot

Figure 4: Aperture-Coupled Feed (Basal and Gupta, 2020, Kashyap *et al.*, 2022)

Proximity-Coupled Feed Antenna

The following are the details of this feeding technique (Gupta *et al.*, 2023):

- i. **Principle**: Proximity-coupled feed is based on placing the feed line in close proximity to the microstrip antenna, either parallel or perpendicular to the radiating patch. Energy is coupled capacitively or inductively between the feed line and the antenna. Figure 5 shows proximity-coupled feed antenna.
- ii. **Reduced Feed Line Interference:** Proximity coupling minimizes interference between the feed line and the radiating element. This technique is

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

advantageous when preserving the antenna's radiation characteristics is a priority.

iii. **Design Flexibility:** Engineers can adjust the distance and orientation of the feed line relative to the antenna to fine-tune the coupling mechanism and achieve the desired performance.

iv. **Applications:** Proximity-coupled feed is suitable for microstrip antenna designs where reduced interference and precise control over coupling are essential (Ramos *et al.*, 2022).



Figure 5: Proximity-Coupled Feed Antenna (Gupta *et al.*, 2023)

Inverted Microstrip Feed

The following are the details of this feeding technique:

i. **Principle:** In the inverted microstrip feed technique, the feed line is located on the top side of the dielectric substrate, while the radiating patch is on the bottom side. Energy is coupled from the feed line to the patch through the substrate. Figure 6 shows a sample of inverted microstrip feed antenna (Mahatmanto *et al.*, 2022).



Figure 6: Inverted Microstrip Feed (Mahatmanto *et al.*, 2022)

ii. **Broadband Impedance Matching:** This technique is particularly useful for achieving broadband impedance matching, making it suitable for multiband applications.

iii. **Compact Design:** Inverted microstrip feed allows for a compact antenna design, as the feed line is integrated into the top surface of the substrate.

iv. **Applications:** Inverted microstrip feed is applied in situations where a compact, broadband antenna design with effective impedance matching is required, such as in wireless communication systems and multiband antennas.

Aperture-Backed Slot Feed

The following are the details of this feeding technique (Christina, 2021):

i. Principle: The Aperture-Backed Slot Feed technique involves cutting a slot or aperture into the microstrip patch antenna itself. Energy is then fed from the microstrip transmission line through this slot to the radiating element.

ii. Wide Bandwidth: This feeding technique is particularly common in slot antennas due to its ability to provide wide bandwidth. The slot dimensions can be adjusted to achieve the desired bandwidth.

iii. Radiation Characteristics: Aperture-backed slot antennas typically exhibit radiation patterns determined by the slot dimensions, making them suitable for various applications requiring specific radiation characteristics.

iv. Applications: Aperture-backed slot feed is employed in communication systems and radar applications that require wide bandwidth and tailored radiation patterns.

Coplanar Waveguide (CPW) Feed

The following are the details of this feeding technique (Christina, 2021, Shereen *et al.*, 2022):

i. **Principle:** CPW feed involves the use of Coplanar Waveguide transmission lines to feed the microstrip antenna. CPW transmission lines consist of a central conductor flanked by two ground planes, all on the same substrate. Figure 7 shows a framework of CPW.



Figure 7: CPW Antenna Feed (Christina, 2021)

ii. **Low-Loss Characteristics**: CPW feed lines are known for their low-loss properties, making them ideal for applications where signal integrity and minimal losses are crucial.
iii. **Integration:** CPW feed lines can be conveniently integrated with other microwave components, making them suitable for complex systems.
iv. **Applications:** CPW feed is preferred in high-frequency applications, such as millimeter-wave communication systems and phased array antennas, where low-loss transmission is vital.

Balanced Feed

The following are the details of this feeding technique (Chritina, 2021, Mishra *et al.,* 2022):

i. **Principle:** Balanced feed structures are employed to reduce common-mode radiation and improve antenna performance in specific cases. Techniques like the balanced microstrip feed can be utilized.
ii. **Common-Mode Radiation Reduction**: Balanced feed configurations minimize common-mode currents and radiation, which can lead to enhanced antenna performance, especially in systems sensitive to interference.
iii. **Applications:** Balanced feeds find application in scenarios where electromagnetic compatibility (EMC) and interference mitigation are paramount, such as in sensitive receivers or systems operating in close proximity to other electronic devices.

REVIEW OF WORKS

A lot of works is ongoing to investigate the performance of microstrip antenna based on various feeding techniques.

Tasnim *et al.,* (2019) paper featured a comparative performance investigation of circular and elliptical microstrip patch antennas, along with their arrays, using diverse feeding techniques at an X-band frequency. The resonant frequency was set at 10 GHz, known for its various applications in wireless communication. Design and simulation were conducted using CST Microwave Studio. It was established that microstrip line feeding displayed superior performance in terms of gain and directivity when compared to coaxial probe feeding. The proposed model within the paper consisted of an antenna with an area of 3558.12 mm^2 and a 2×4 array of circular patches employing line feed, resulting in 16.2 dB gain, 16.4 dB directivity, and 94.42% efficiency.

Bansa and Gupta, (2020) paper provides an extensive examination of various Microstrip antennas and their associated feeding techniques, shedding light on their advantages and applications when compared to traditional antennas. It encompasses a comprehensive overview of how Microstrip antennas have evolved as a compelling alternative to conventional antenna designs. This study aims to elucidate the diverse range of Microstrip antenna configurations and feeding methods and how they have revolutionized the field of wireless communication and microwave technology. By delving into this subject, the

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

paper offers valuable insights into the enhanced performance, compactness, and versatility that Microstrip antennas bring to the table. Furthermore, it scrutinizes the impact of different feeding techniques on the overall efficiency and functionality of these antennas, elucidating why they have garnered significant attention in recent years. The analysis serves as a valuable resource for researchers, engineers, and enthusiasts seeking to comprehend the transformative potential of Microstrip antennas in modern communication systems.

Kashyap *et al.,* (2022) paper conducted a comprehensive review of multiple feeding techniques employed to excite microstrip patch antennas, including inset feed, co-axial feed, aperture feed, proximity feed, and CPW feed. The primary objective was to enhance the performance of these antennas concerning key parameters such as S11 parameter, bandwidth, gain, and radiation pattern, making them better suited for various wireless communication applications. During the investigation, a thorough examination of these feeding processes was undertaken, with a particular focus on their historical utilization and effectiveness. The paper aimed to shed light on how these techniques have evolved and contributed to optimizing microstrip patch antennas for diverse applications within the realm of wireless communication. By presenting this information, the paper provided a valuable resource for researchers and practitioners seeking to understand the past developments and achievements in the field of microstrip patch antenna feeding techniques. This historical perspective served as a foundation for appreciating the continuous advancements made in antenna design to meet the evolving demands of wireless communication systems.

Ramos and Cerreno, (2022) proposed a novel analytical model was presented for estimating the impedance characteristics of proximity-coupled microstrip patch antennas when excited by a differential feed network. Extensive validation of this model was conducted within the S- and X-bands. The outcomes of the validation process revealed that the proposed model provided highly accurate estimations of impedance response across a broad frequency spectrum encompassing both bands. This significant development facilitated the analytical modeling of differentially-fed microstrip patch antennas, catering to the requirements of radar and communication systems demanding substantial bandwidth and exceptional polarization purity.

Mahatmanto *et al.,* (2022) developed a novel feeding mechanism for a parabolic receiving antenna system, aimed at receiving Himawari-8 satellite data at the Remote Sensing Ground Station. Conventional parabolic antenna systems typically employ a horn antenna fed by a monopole. In contrast, this research introduced the concept of a horn antenna fed by a trapezoid microstrip patch to achieve a higher-gain antenna system. The inverted trapezoid microstrip patch antenna demonstrated a gain of approximately 7.6 dB at a frequency of 4.148 GHz. When integrated with the flared horn, referred to as the feed antenna, the combined gain reached 15.8 dB at the same frequency. The return loss characteristics of the combined antenna exhibited a frequency bandwidth spanning from 4.023 to 4.212 GHz, with a threshold of -10 dB. The overall gain achieved by the feed antenna in conjunction with the 2.4-meter parabolic reflector amounted to approximately 34.9 dB at a frequency of 4.148 GHz.

Gupta *et al.,* (2023) paper introduced a novel proximity-coupled antenna designed for IoT (Internet of Things) devices, featuring dual radiators and an inverted L-shaped feed line.

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

To achieve a broad impedance bandwidth for this antenna, several modifications were implemented. This included the incorporation of a V-shaped slot in the radiator and the introduction of a parasitic patch. The dual radiating elements, combined with the coupled feed line, played a crucial role in expanding the antenna's bandwidth, ultimately reaching 220 MHz within the frequency range of 2.37 to 2.59 GHz. This bandwidth was well-suited for applications such as Ingenu-RPMA, Bluetooth, and the ISM band (2.4–2.4835 GHz). The antenna demonstrated its versatility by being compatible with various IoT platforms while maintaining stable impedance and radiation characteristics. Additionally, the paper explored the deployment of the antenna on different materials, including muscle tissue for wearable devices, glass, and wood surfaces for IoT applications. Although a slight deviation of 30 MHz was observed, it fell within an acceptable range for the antenna's broad spectrum of operation. Moreover, the radiation pattern exhibited robust performance in both the E-plane and H-plane, achieving a maximum gain of 6.37 dBi on muscle tissue and a minimum of 4.47 dBi on glass surfaces. In terms of safety, the antenna adhered to specific absorption rate (SAR) requirements, with a SAR value of 0.326W/kg, ensuring the protection of human tissues from electromagnetic radiation. Overall, the proximity-coupled dual radiator antenna offered a compact and easily integrable solution for various IoT applications.

COMPARATIVE ANALYSIS OF MICROSTRIP ANTENNA FEEDING TECHNIQUES

In the study of microwave frequency communication and radiation, the concept of microstrip antenna feeding techniques emerges as a critical component in the arsenal of engineers and antenna designers. These feeding techniques encapsulate an array of methods and configurations that serve a singular purpose – to efficaciously deliver energy or signals into microstrip antennas. Their significance cannot be overstated, for they wield the power to sculpt the antenna's performance, influence impedance matching, shape radiation characteristics, and orchestrate its overall effectiveness. At the heart of this technological orchestra lies the microstrip antenna, often affectionately referred to as the patch antenna. This class of antennas is renowned for its planar, compact, and lightweight design, which aligns seamlessly with the demands of modern microwave communication systems. These antennas are entrusted with the task of transmitting and receiving signals across a diverse range of applications, spanning from telecommunications to satellite communication and radar systems. To execute these tasks with precision, the methods employed to feed these antennas become pivotal.

The crux of the matter is that the selection of an appropriate feeding technique for a microstrip antenna is not a one-size-fits-all endeavor. Instead, it hinges upon a medley of design prerequisites and operational criteria. The diverse landscape of microstrip antenna feeding techniques and unearth the fundamental tenets guiding their selection are as follows:

1. **Frequency of Operation**: The frequency at which a microstrip antenna operates is a cardinal factor. Whether it's the ultra-high frequencies of millimeter-wave communication or the more commonplace microwave bands, each frequency regime necessitates a feeding technique tailored to its unique characteristics.
2. **Bandwidth Requirements:** Some applications require antennas with broad bandwidth capabilities to accommodate a wide range of frequencies. Others, with

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

more specific bandwidth constraints, demand feeding techniques that can deliver optimal performance within those confines.

3. **Impedance Matching:** Achieving impedance matching between the feedline and the antenna is a perpetual pursuit. Some feeding techniques excel in this regard, ensuring minimal signal reflection and maximum power transfer.
4. **Radiation Pattern Control:** The desired radiation pattern can vary from application to application. Certain feeding techniques can sculpt radiation patterns to meet specific needs, whether it's directional, omnidirectional, or tailored beam patterns.
5. **Integration Constraints:** The feasibility of integrating the feeding technique into the overall system architecture plays a pivotal role. Some applications necessitate a seamless fit within constrained spaces or complex assemblies.

A comparative analysis of microstrip antenna feeding techniques is given in table 1.

Table 1: Comparative Analysis of Microstrip Antenna Feeding Techniques

Feeding Technique	Advantages	Disadvantages	Typical Applications	Principle of Operation
Coaxial Feed	- Simplicity	- Impedance matching challenges	Broadband communication	Direct connection via coaxial cable
Microstrip Line Feed	- Better impedance matching	- Limited bandwidth	Patch antennas	Use of microstrip transmission line for energy delivery
Aperture-Coupled Feed	- Good impedance matching	- Sensitive to positioning	Phased array antennas, radar	Energy coupling through an aperture or slot in ground plane
Proximity-Coupled Feed	- Reduced interference	- Requires careful tuning	Small form-factor devices	Close placement of feed line to antenna element
Inverted Microstrip Feed	- Broadband impedance matching	- Complex design	Broadband and multiband	Inverted configuration with feed line on top of substrate

MICROSTRIP ANTENNA TECHNIQUES FOR 5G AND BEYOND APPLICATION

Table 2 highlights current and future research areas for 5G and beyond, particularly in the context of Microstrip Antenna Feeding Techniques. The table provides an overview of current research areas and future directions related to Microstrip Antenna Feeding Techniques (MAFT) in the context of 5G and beyond. Researchers and engineers are actively exploring these areas to improve the performance, efficiency, and coverage of wireless communication systems.

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

Table 2: Microstrip Antenna Feeding Techniques Current and Future Research Areas For 5G And Beyond

Research Area	Description and Focus	Current Progress	Future Research Directions
Advanced Feeding Techniques	Exploration of novel feeding methods for enhanced performance	Ongoing research on various feeding techniques and their integration in 5G systems	Investigation into metamaterial-based feeding, advanced polarization techniques, and efficiency improvement strategies
Millimeter-Wave and Terahertz	Extending frequency bands for higher data rates	Active deployment of mmWave technology in 5G	Development of efficient antennas for even higher frequency bands, e.g., Terahertz
Beamforming and MIMO	Utilizing beamforming and massive MIMO for improved coverage and capacity	Integration of beamforming and MIMO in 5G networks	Optimization of beamforming algorithms, hybrid beamforming, and further enhancing MIMO capabilities
Miniaturization and Integration	Reducing antenna size while maintaining performance	Shrinking antenna sizes for compact devices	Research on compact, multiband antennas and integration with other components
Energy Efficiency	Developing energy-efficient antenna solutions	Improvements in energy-efficient antennas	Investigation into energy harvesting techniques, reconfigurable antennas for energy savings
Antenna Arrays and Massive MIMO	Utilizing large antenna arrays for high-capacity networks	Implementation of Massive MIMO in 5G base stations	Exploring massive MIMO in indoor and IoT scenarios, optimization of array configurations
Smart Antennas and Adaptive Systems	Adapting antenna characteristics based on environment and user requirements	Integration of adaptive antennas in 5G systems	Research on AI-driven adaptive antennas, cognitive radio systems
Hybrid Satellite-Terrestrial Systems	Combining satellite and terrestrial communication for global coverage	Development of hybrid systems for rural and remote connectivity	Advancements in seamless handovers, optimization of hybrid network architectures
Security and Privacy	Enhancing security and privacy in antenna communications	Ongoing research in secure communication techniques	Investigating quantum-safe communication methods, privacy-preserving antenna design
mmWave Phased Array Antennas	Developing efficient beamforming at mmWave frequencies	Prototyping phased arrays for mmWave bands	Research on low-cost mmWave antennas, array calibration techniques

CONCLUSION

In conclusion, the field of Microstrip Antenna Feeding Techniques (MAFT) is poised to play a pivotal role in the ongoing development and future evolution of wireless communication systems, particularly in the era of 5G and beyond. With an array of

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]

innovative research areas spanning advanced feeding techniques, millimeter-wave and Terahertz exploration, beamforming and MIMO technologies, miniaturization and integration, energy efficiency, antenna arrays, smart antennas, hybrid satellite-terrestrial systems, security and privacy enhancements, and mmWave phased array antennas, the landscape of wireless communication is rapidly advancing.

These diverse research domains collectively drive the optimization of antenna performance, coverage, and energy efficiency while addressing the unique challenges posed by emerging communication scenarios. As technology continues to progress, researchers and engineers are dedicated to creating efficient, compact, and adaptable antennas capable of meeting the ever-increasing demands for high-speed data transmission, low-latency connectivity, and secure communication.

The future promises exciting developments in Microstrip Antenna Feeding Techniques, ushering in an era of enhanced wireless connectivity that empowers a wide range of applications, from urban networks to remote areas and from IoT devices to intelligent transportation systems. The ongoing pursuit of cutting-edge solutions and the collaboration between academia and industry will undoubtedly shape the wireless communication landscape, bringing us closer to the seamless connectivity envisioned in the 5G and beyond era.

REFERENCES

Bansal, A., & Gupta, R. (2020). A review on microstrip patch antenna and feeding techniques. *International Journal of Information Technology*, *12*, 149-154.

Christina, G. (2021). A review on microstrip patch antenna performance improvement techniques on various applications. *Journal of Trends in Computer Science and Smart Technology*, *3*(3), 175-189.

Gupta, A., Gupta, V. K., Bansal, S., & Sharma, A. (2023, January). Broadband Proximity Coupled Antenna for IoT Applications. In *2023 International Conference for Advancement in Technology (ICONAT)* (pp. 1-4). IEEE.

Kashyap, N., Singh, D., & Sharma, N. (2022). Comprehensive Study of Microstrip Patch Antenna Using Different Feeding Techniques. *ECS Transactions*, *107*(1), 9545.

Mahatmanto, B. P. A., Irawadi, D., Imdad, M. T., Jatmiko, N. W., Gunawan, H., & Apriono, C. (2022, August). High Gain Inverted Trapezoid Microstrip Patch Antenna Combined with Flared Horn. In *2022 9th International Conference on Information Technology, Computer, and Electrical Engineering (ICITACEE)* (pp. 169-172). IEEE.

Mishra, B., Verma, R. K., Yashwanth, N., & Singh, R. K. (2022). A review on microstrip patch antenna parameters of different geometry and bandwidth enhancement techniques. *International Journal of Microwave and Wireless Technologies*, *14*(5), 652-673.

Ramos, N. R. C., & Salazar-Cerreno, J. L. (2022, April). A New Impedance Model for Differentially-fed Proximity-Coupled Microstrip Patch Antennas. In *2022 IEEE Texas Symposium on Wireless and Microwave Circuits and Systems (WMCS)* (pp. 1-5). IEEE.

Shereen, M. K., Khattak, M. I., & Nebhen, J. (2022). A review of achieving frequency reconfiguration through switching in microstrip patch antennas for future 5G applications. *Alexandria Engineering Journal*, *61*(1), 29-40.

Tasnim, N., Inum, R., Khatun, H., & Khan, M. A. G. (2019, January). Comparative Study on Circular and Elliptical Microstrip Patch Antenna Arrays with Microstrip Line and Coaxial Probe Feeding for X-band. In *2019 International Conference on Robotics, Electrical and Signal Processing Techniques (ICREST)* (pp. 74-78). IEEE.

EDITOR-IN-CHIEF
Prof. H. U. Nwanjo [Nigeria]